


Voltage Transducer LV 25-P/SP5

For the electronic measurement of voltages : DC, AC, pulsed..., with a galvanic isolation between the primary circuit (high voltage) and the secondary circuit (electronic circuit).



$$I_{PN} = 10 \text{ mA}$$

$$V_{PN} = 10 \dots 1500 \text{ V}$$



Electrical data

I_{PN}	Primary nominal r.m.s. current	10	mA			
I_p	Primary current, measuring range	0 .. ± 14	mA			
R_M	Measuring resistance	$R_{M \min}$	$R_{M \max}$			
		with $\pm 15 \text{ V}$	@ $\pm 10 \text{ mA}_{\max}$	100	340	Ω
			@ $\pm 14 \text{ mA}_{\max}$	100	180	Ω
I_{SN}	Secondary nominal r.m.s. current	25	mA			
K_N	Conversion ratio	2500 : 1000				
V_C	Supply voltage ($\pm 5 \%$)	± 15	V			
I_C	Current consumption	$10 + I_s$	mA			
V_d	R.m.s. voltage for AC isolation test, 50 Hz, 1 mn	4.2	kV			

Accuracy - Dynamic performance data

X_G	Overall Accuracy @ I_{PN} , $T_A = 25^\circ\text{C}$	± 0.8	%		
ϵ_L	Linearity	< 0.2	%		
I_O	Offset current @ $I_p = 0$, $T_A = 25^\circ\text{C}$	Typ	Max		
			± 0.15	mA	
I_{OT}	Thermal drift of I_O	- $25^\circ\text{C} \dots + 85^\circ\text{C}$	± 0.25	± 0.50	mA
		- $40^\circ\text{C} \dots + 85^\circ\text{C}$	± 0.30	± 0.80	mA
t_r	Response time ¹⁾ @ 90 % of V_{PN}	25	μs		

General data

T_A	Ambient operating temperature	- 40 .. + 85	$^\circ\text{C}$
T_S	Ambient storage temperature	- 50 .. + 90	$^\circ\text{C}$
R_p	Primary coil resistance @ $T_A = 85^\circ\text{C}$	300	Ω
R_s	Secondary coil resistance @ $T_A = 85^\circ\text{C}$	117	Ω
m	Mass	22	g
	Standards	EN 50155 : 1995	

Features

- Closed loop (compensated) voltage transducer using the Hall effect
- Insulated plastic case recognized according to UL 94-V0.

Special features

- $V_d = 4.2 \text{ kV}$ (4 kV DC/5 mn)
- $T_A = -40^\circ\text{C} \dots + 85^\circ\text{C}$
- Railway equipment.

Principle of use

- For voltage measurements, a current proportional to the measured voltage must be collected through an external resistor R_1 which is selected by the user and installed in series with the primary circuit of the transducer.

Advantages


- Excellent accuracy
- Very good linearity
- Low thermal drift
- Low response time
- High bandwidth
- High immunity to external interference
- Low disturbance in common mode.

Applications

- AC variable speed drives and servo motor drives
- Static converters for DC motor drives
- Battery supplied applications
- Uninterruptible Power Supplies (UPS)
- Power supplies for welding applications.

Note : ¹⁾ $R_1 = 25 \text{ k}\Omega$ (L/R constant, produced by the resistance and inductance of the primary circuit).

Dimensions LV 25-P/SP5 (in mm. 1 mm = 0.0394 inch)



Mechanical characteristics

- General tolerance $\pm 0.2\text{ mm}$
- Fastening & connection of primary 2 pins
0.635 x 0.635 mm
- Fastening & connection of secondary 3 pins $\varnothing 1\text{ mm}$
- Recommended PCB hole 1.2 mm

Remark

- I_s is positive when V_p is applied on terminal +HT.

Instructions for use of the voltage transducer model LV 25-P/SP5

Primary resistor R_1 : the transducer's optimum accuracy is obtained at the nominal primary current. As far as possible, R_1 should be calculated so that the nominal voltage to be measured corresponds to a primary current of 10 mA.

Example: Voltage to be measured $V_{PN} = 250\text{ V}$

- a) $R_1 = 25\text{ k}\Omega / 2.5\text{ W}$, $I_p = 10\text{ mA}$ Accuracy = $\pm 0.8\%$ of V_{PN} (@ $T_A = +25^\circ\text{C}$)
b) $R_1 = 50\text{ k}\Omega / 1.25\text{ W}$, $I_p = 5\text{ mA}$ Accuracy = $\pm 1.6\%$ of V_{PN} (@ $T_A = +25^\circ\text{C}$)

Operating range (recommended) : taking into account the resistance of the primary windings (which must remain low compared to R_1 , in order to keep thermal deviation as low as possible) and the isolation, this transducer is suitable for measuring nominal voltages from 10 to 1500 V.

LEM reserves the right to carry out modifications on its transducers, in order to improve them, without previous notice.